



Figure 5B-7. 1959-62 Sportster CH - Wiring Diagram

WIRING

1959-62 SPORTSTER CH

WIRING DIAGRAM KEY

- | | |
|---|--|
| <p>A. Conduit (One wire) - Black</p> <p>B. Conduit (One wire) - Black</p> <p>C. Conduit (Two wires) - Red and green wires</p> <p>D. Conduit (One wire) - Red</p> <p>E. Conduit (Two wires) - Red and green wires</p> <p>F. Conduit (Two wires) - Red and green wires</p>
<p>1. Horn Switch - Black wire</p> <p>2. Headlamp - Black and red wires</p> <p>3. Ignition Cutout Switch - Black wire</p> <p>4. Generator -
 "F" Terminal - Green wire
 "A" Terminal - Red wire</p> <p>5. Headlamp Switch -</p> | <p>Terminal "B" - Red wire</p> <p>Terminal 1 - Green wire</p> <p>Terminal 2 - Red wire</p> <p>Terminal 3 - Black wire</p> <p>6. Fuse - Two green wires</p> <p>7. Voltage Regulator -
 "F" Terminal - Green wire
 "GEN" Terminal - Red wire
 "BAT" Terminal - Red wire</p> <p>8. Magneto - Black wire</p> <p>9. Stoplight Switch - Two red wires</p> <p>10. Tail and Stop Lamp - Red and green wires</p> <p>11. Horn -
 Upper Terminal - Black wire
 Lower Terminal - Three red wires</p> |
|---|--|